

Rema radio remote control for cranes, hoists and winches

Product information



The Rema radio remote control system provides safe and user-friendly operation from a distance, ideal for lifting and hoisting applications. With external certification SIL2, PLd safety level and a 2.4 GHz frequency (worldwide license-free), it complies with the highest safety standards. The receiver is easy to install and ready for immediate use. Replacing a transmitter is quick and requires no opening, ensuring flexibility and convenience. Wireless control increases mobility and eliminates the risk of cable damage, improving safety, visibility, and efficiency.

Features

- Compact, robust, and waterproof design (IP65)
- Equipped with an independently PLd-certified emergency stop
- Operating range of 200+ meters in open area
- Single and dual speed control
- Operating temperature: -20 °C to +55 °C

Versions

- Lifting/lowering
- Lifting/lowering + trolley travel
- Lifting/lowering + trolley and crane travel

Standard delivery

- 1 handheld transmitter incl. battery holder and 3 disposable 1.5 V (AAA) batteries
- 1 receiver 12-24 V AC/DC or 48-230 V AC
- 1 protective foil adapted to the application

Options

- Charging set: table charger, 2 rechargeable batteries, and adapter* ... [Read more](#)

Rema radio remote control for cranes, hoists and winches

Technical data

Part code	Model	Dimensions Transmitter LxWxH mm	Function	Number of speed	Dimensions Receiver LxWxH mm	Weight kg
0726001	MX8D-24V-2 H/S	85 x 193 x 43	lifting/lowering	2	120 x 117 x 51	0.28
0726003	MX8C-24V-2 H/S/KA	85 x 193 x 43	lifting/lowering/trolley travel	2	120 x 117 x 51	0.28
0726005	MX8B-24V-2 H/S/KA/KR	85 x 193 x 43	lifting/lowering/trolley/crane travel	2	120 x 117 x 51	0.28
0726011	MX8G-24V-1 H/S	85 x 193 x 43	lifting/lowering	1	120 x 117 x 51	0.28
0726013	MX8F-24V-1 H/S/KA	85 x 193 x 43	lifting/lowering/trolley travel	1	120 x 117 x 51	0.28
0726015	MX8H-24V-1 H/S/KA/KR	85 x 193 x 43	lifting/lowering/trolley/crane travel	1	120 x 117 x 51	0.28
0726034	RECHARGEABLE BATTERY SET	-	charging	-	-	-